1 –

SCOMPATTARE IL FILE GAN9.8U6X-4-GD.MTN-LKW300-IT.EN.rar SUL VOSTRO DESKTOP

2-

APRIRE UN BROWSER E INSERIRE COME INDIRIZZO 192.168.1.1

3- INSERIRE USERNAME E PASSWORD (admin – admin)



4 –

ENTRATE NELLA TAB ADMIN

LINK	Red Line	Wireless Periph	erals				
Admin	Wizard	Status	Network	Service	Advanced	Admin	Diagnostic
	Commit/Reboot U	odate Log	Password	Time Logout			
Commit/Reboot	Commit/R This page is used to	eboot commit changes to system r	nemory and reboot your sy	stem with different configurations.			
	Reboot from: Sav	ve Current Configuration 💌)				
	Commiconarges						

5 –

ENTRATE NELLA TAB UPDATE

LWK	Red Line W	/ireless Periph	erals									
Update	Wizard	Status	Network	Service	Advanced	Admin	Diagnostic					
Upgrade Firmware Backup/Restore	Upgrade Fi	rmware	Password	Time Logout								
	This page allows you upgrade the ADSL Router firmware to new version. Please note, do not power off the device during the upload because it may crash the system. Note: System will reboot after file is uploaded.											
	Select File:		Sfoglia									
	Upload Reset											

6 –

CLICCATE SU SFOGLIA E ANDATE A SELEZIONARE IL FILE

GAN9.8U6X-4-GD.MTN-R6B022-IT.EN_update.IMG CHE AVETE PRECEDENTEMENTE SCOMPATTATO SUL VOSTRO DESKTOP

7 –

CLICCATE SU UPDATE E ATTENDETE IL COMPLETAMENTO DELL'OPERAZIONE

ATTENZIONE!!!!!

NON SPEGNETE IL DISPOSITIVO DURANTE L'OPERAZIONE DI UPDATE